




## 



## HSA-275/3+0 M

- Surge arresters type T2+T3 ensure the equipotential bonding and reduce switching, induced and residual overvoltage in LV power supply systems.
- The products consist of varistors with big discharge ability.
- Configurations 1+1 and 3+1 are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Installed at the boundaries of LPZ 1 LPZ 3 into subsidiary switchboards and control panels.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- S indication specifies a version with remote monitoring.

| Test class according to EN 61643-11:2012 (IEC 61643-11:2011)<br>System<br>Number of poles<br>Rated operating AC voltage<br>Maximum continuous operating voltage AC<br>Maximum discharge current (8/20)<br>Nominal discharge current for class II test (8/20)<br>Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub> | U <sub>N</sub><br>U <sub>C</sub><br>I <sub>max</sub><br>I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub><br>U <sub>p</sub> | T2, T3<br>TN-C<br>3<br>230 V<br>275 V<br>50 kA<br>20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV |
|--|---|---|
| Number of poles<br>Rated operating AC voltage<br>Maximum continuous operating voltage AC<br>Maximum discharge current (8/20)<br>Nominal discharge current for class II test (8/20)<br>Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub>   | U <sub>C</sub><br>I <sub>max</sub><br>I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub>                                     | 3<br>230 V<br>275 V<br>50 kA<br>20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV                   |
| Rated operating AC voltageMaximum continuous operating voltage ACMaximum discharge current (8/20)Nominal discharge current for class II test (8/20)Open circuit voltage of the combination wave generatorTotal discharge current (8/20) L1+L2+L3->PENVoltage protection level at In  | U <sub>C</sub><br>I <sub>max</sub><br>I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub>                                     | 230 V<br>275 V<br>50 kA<br>20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV                        |
| Maximum continuous operating voltage AC<br>Maximum discharge current (8/20)<br>Nominal discharge current for class II test (8/20)<br>Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub>  | U <sub>C</sub><br>I <sub>max</sub><br>I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub>                                     | 275 V<br>50 kA<br>20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV                                 |
| Maximum discharge current (8/20)<br>Nominal discharge current for class II test (8/20)<br>Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub>   | I <sub>max</sub><br>I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub>   | 50 kA<br>20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV  |
| Nominal discharge current for class II test (8/20)<br>Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub>   | I <sub>n</sub><br>U <sub>OC</sub><br>I <sub>Total</sub><br>U <sub>p</sub>   | 20 kA<br>6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV   |
| Open circuit voltage of the combination wave generator<br>Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at I <sub>n</sub>   | U <sub>oc</sub><br>I <sub>Total</sub><br>U <sub>p</sub><br>U <sub>p</sub>   | 6 kV<br>150 kA<br>< 1.25 kV<br>< 0.85 kV  |
| Total discharge current (8/20) L1+L2+L3->PEN<br>Voltage protection level at In   | I <sub>Total</sub><br>U <sub>p</sub><br>U <sub>p</sub>  | 150 kA<br>< 1.25 kV<br>< 0.85 kV  |
| Voltage protection level at In   | U <sub>p</sub><br>U <sub>p</sub>  | < 1.25 kV<br>< 0.85 kV  |
|  | U <sub>p</sub>  | < 0.85 kV   |
|  |   |   |
| Voltage protection level at U <sub>oc</sub>  | Uτ  | 0071/   |
| Temporary overvoltage test (TOV) for $t_T = 5 \text{ s}$   |   | 337 V   |
| Temporary overvoltage test (TOV) for $t_T = 120$ min   | U <sub>T</sub>  | 440 V   |
| Response time  | t <sub>A</sub>  | < 25 ns   |
| Maximal back-up fuse   |   | 160 A gL/gG   |
| Residual current   | I <sub>PE</sub>   | ≤ 200 μA  |
| Short-circuit current rating at maximum back-up fuse   | I <sub>SCCR</sub>   | 60 kA <sub>rms</sub>  |
| Lightning protection zone  |   | LPZ 1-2, LPZ 2-3  |
| Housing material   |   | Polyamid PA6, UL94 V-0  |
| Degree of protection   |   | IP20  |
| Operating temperature  | θ   | -40 ÷ 70 °C   |
| Humidity range   | RH  | 5 ÷ 95 %  |
| Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2  | S   | 2.5 mm <sup>2</sup> (L, N)<br>6 mm <sup>2</sup> (PE, PEN)   |
| Clamp fastening range (solid conductor)  |   | $1.5 \div 25 \text{ mm}^2$  |
| Clamp fastening range (stranded conductor)   |   | $1.5 \div 16 \text{ mm}^2$  |
| Tightening moment  |   | 3 Nm  |
| Installation   |   | On DIN rail 35 mm   |
| Modular width  |   | 3 TE  |

## Surge arresters T2+T3




| Туре   |   | HSA-275/3+0 M                           |
|--|---|---|
| Operating position   |   | Any                                     |
| Product placement environment  |   | Internal                                |
| Signalling at the device   |   | Optic                                   |
| Importance of local signaling  |   | OK – clear target<br>FAULT – red target |
| Remote signalling  |   | No                                      |
| Modular design   |   | Yes                                     |
| Article number of spare module   |   | 27 086                                  |
| Lifetime   |   | > 100 000 h                             |
| Designed according to standards  |   |   |
| Requirements and test methods for SPDs connected to low-voltage power systems        |   | IEC 61643-11:2011                       |
| Safety of Flammability of Plastic Materials  |   | UL 94                                   |
| Application standards  |   |   |
| Protection against lightning   |   | IEC 62305:2010                          |
| Selection and erection of electrical equipment - Switchgear and controlgear          |   | HD 60364-5-53:2022                      |
| Selection and application principles for SPDs connected to low-voltage power systems |   | CLC/TS 61643-12:2009                    |
| Ordering, packaging and additional data  |   |   |
| Mass   | m | 315 g                                   |
| Mass (including the packaging)   | m | 339 g                                   |
| Packaging dimensions (H x W x D)   |   | 60 x 113 x 73 mm                        |
| Packaging value  | V | 0.5 dm <sup>3</sup>                     |
| ETIM group   |   | EG000021                                |
| ETIM class   |   | EC000941                                |
| Customs tariff no.   |   | 85363010                                |
| EAN code   |   | 8590681115992                           |
| Art. number  |   | 27 083                                  |



**The link in the QR code** leads to the online presentation of the **HSA-275/3+0 M**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com** 



## Application wiring diagram (installation)



Internal diagram

