

HSA-440/4+0 M

- Surge arresters type T2+T3 ensure the equipotential bonding and reduce switching, induced and residual overvoltage in LV power supply systems.
- The products consist of varistors with big discharge ability.
- Configurations 1+1 and 3+1 are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Installed at the boundaries of LPZ 1 LPZ 3 into subsidiary switchboards and control panels.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- **S** indication specifies a version with remote monitoring.

Test class according to EN 61643-11:2012 (IEC 61643-11:2011) System Number of poles Rated operating AC voltage Maximum continuous operating voltage AC Maximum discharge current (8/20) Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min Response time	U_N	T2, T3 TN-S
Number of poles Rated operating AC voltage Maximum continuous operating voltage AC Maximum discharge current (8/20) Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $I_T = 5$ s Temporary overvoltage test (TOV) for $I_T = 120$ min		
Rated operating AC voltage Maximum continuous operating voltage AC Maximum discharge current (8/20) Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min	- 11	
Maximum continuous operating voltage AC Maximum discharge current (8/20) Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min	1.1	4
Maximum discharge current (8/20) Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min	O_N	400 V
Nominal discharge current for class II test (8/20) Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $I_T = 5$ s Temporary overvoltage test (TOV) for $I_T = 120$ min	U_{C}	440 V
Open circuit voltage of the combination wave generator Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min	I _{max}	40 kA
Total discharge current (8/20) L1+L2+L3+N->PE Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5$ s Temporary overvoltage test (TOV) for $t_T = 120$ min	I _n	15 kA
Voltage protection level at I_n Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5 \text{ s}$ Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	U_{oc}	6 kV
Voltage protection level at U_{OC} Temporary overvoltage test (TOV) for $t_T = 5 \text{ s}$ Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	I _{Total}	160 kA
Temporary overvoltage test (TOV) for $t_T = 5 \text{ s}$ Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	U_p	< 1.8 kV
Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	U_p	< 1.4 kV
	U_T	580 V
Response time	U _T	762 V
	t _A	< 25 ns
Maximal back-up fuse		160 A gL/gG
Residual current	I_{PE}	≤ 400 μA
Short-circuit current rating at maximum back-up fuse	I_{SCCR}	60 kA _{rms}
Lightning protection zone		LPZ 1-2, LPZ 2-3
Housing material		Polyamid PA6, UL94 V-0
Degree of protection		IP20
Operating temperature	9	-40 ÷ 70 °C
Humidity range	RH	5 ÷ 95 %
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2	S	2.5 mm ² (L, N) 6 mm ² (PE, PEN)
Clamp fastening range (solid conductor)		1.5 ÷ 25 mm ²
Clamp fastening range (stranded conductor)		1.5 ÷ 16 mm ²
Tightening moment		3 Nm
Installation		On DIN rail 35 mm
Modular width		




Туре		HSA-440/4+0 M
Operating position		Any
Product placement environment		Internal
Signalling at the device		Optic
Importance of local signaling		OK – clear target FAULT – red target
Remote signalling		No
Modular design		Yes
Article number of spare module		27 194
Lifetime		> 100 000 h
Designed according to standards		
Requirements and test methods for SPDs connected to low-voltage power systems		IEC 61643-11:2011
Safety of Flammability of Plastic Materials		UL 94
Application standards		
Protection against lightning		IEC 62305:2010
Selection and erection of electrical equipment – Switchgear and controlgear		HD 60364-5-53:2022
Selection and application principles for SPDs connected to low-voltage power systems		CLC/TS 61643-12:2009
Ordering, packaging and additional data		
Mass	m	444 g
Mass (including the packaging)	m	472 g
Packaging dimensions (H x W x D)		74 x 112 x 73 mm
Packaging value	V	0.61 dm ³
ETIM group		EG000021
ETIM class		EC000941
Customs tariff no.		85363010
EAN code		8590681116692
Art. number		27 544



The link in the QR code leads to the online presentation of the **HSA-440/4+0 M**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com**



Application wiring diagram (installation)



Internal diagram

