

## HLSA12,5-275/2+0 M

- Lightning impulse current and surge arresters type T1+T2+T3.
- The products consist of varistors with big discharge ability.
- HLSA12,5 in configurations 1+1, 3+1 and HLSA12,5G are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Suitable for objects with considerable levels of protection LPL III and LPL IV.
- Installed at the boundaries of LPZ 0 LPZ 1 and higher zones, closest to where overhead line enters the building i.e. in the main distribution boards.
- In case of the installation of a type T1+T2+T3 in the main switchboard, it is also necessary to install type T2 and T3 in any additional distribution boards in the electrical installation.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- **S** indication specifies a version with remote monitoring.

Туре		HLSA12,5-275/2+0 M
Test class according to EN 61643-11:2012 (IEC 61643-11:2011)		T1, T2, T3
System		TN-S
Number of poles		2
Rated operating AC voltage	$U_N$	230 V
Maximum continuous operating voltage AC	U <sub>c</sub>	275 V
Maximum discharge current (8/20)	I <sub>max</sub>	50 kA
Impulse discharge current for class I test (10/350)	I <sub>imp</sub>	12.5 kA
Charge	Q	6.25 As
Specific energy for class I test	W/R	39 kJ/Ω
Total discharge current (10/350) L+N->PE	I <sub>Total</sub>	25 kA
Total discharge current (8/20) L+N->PE	I <sub>Total</sub>	100 kA
Nominal discharge current for class II test (8/20)	l <sub>n</sub>	25 kA
Open circuit voltage of the combination wave generator	U <sub>oc</sub>	6 kV
Voltage protection level at I <sub>n</sub>	$U_p$	< 1.25 kV
Temporary overvoltage test (TOV) for $t_T = 5 s$	$U_{T}$	337 V
Temporary overvoltage test (TOV) for $t_T = 120 \text{ min}$	$U_{T}$	440 V
Response time	t <sub>A</sub>	< 25 ns
Maximal back-up fuse		160 A gL/gG
Residual current	I <sub>PE</sub>	≤ 700 µA
Short-circuit current rating at maximum back-up fuse	I <sub>SCCR</sub>	60 kA <sub>rms</sub>
Lightning protection zone		LPZ 0-1, LPZ 1-2, LPZ 2-3
Housing material		Polyamid PA6, UL94 V-0
Degree of protection		IP20
Operating temperature	9	-40 ÷ 70 °C
Humidity range	RH	5 ÷ 95 %
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T1	S	6 mm² (L, N) 16 mm² (PE, PEN)

## **Lightning and surge arresters T1+T2+T3**



Туре		HLSA12,5-275/2+0 M
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2	S	2.5 mm <sup>2</sup> (L, N) 6 mm <sup>2</sup> (PE, PEN)
Clamp fastening range (solid conductor)		1.5 ÷ 25 mm <sup>2</sup>
Clamp fastening range (stranded conductor)		1.5 ÷ 16 mm <sup>2</sup>
Tightening moment		3 Nm
Installation		On DIN rail 35 mm
Modular width		2 TE
Operating position		Any
Product placement environment		Internal
Signalling at the device		Optic
Importance of local signaling		OK - clear target FAULT - red target
Remote signalling		No
Modular design		Yes
Article number of spare module		16 086
Lifetime		> 100 000 h
Designed according to standards		
Requirements and test methods for SPDs connected to low-voltage power systems		IEC 61643-11:2011
Safety of Flammability of Plastic Materials		UL 94
Application standards		
Protection against lightning		IEC 62305:2010
Selection and erection of electrical equipment – Switchgear and controlgear		HD 60364-5-53:2022
Selection and application principles for SPDs connected to low-voltage power systems		CLC/TS 61643-12:2009
Ordering, packaging and additional data		
Mass	m	290 g
Mass (including the packaging)	m	304 g
Packaging dimensions (H x W x D)		45 x 102 x 74 mm
Packaging value	V	0.34 dm <sup>3</sup>
ETIM group		EG000021
ETIM class		EC001457
Customs tariff no.		85363010
EAN code		8590681114377
Art. number		16 082




**The link in the QR code** leads to the online presentation of the **HLSA12,5-275/2+0 M**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com** 





## Application wiring diagram (installation)



## Internal diagram

